

# Izar-CE AC Charger

Izar is an intelligent AC charger for residential charging use which features a smaller size design with a maximum output of 7kW. With a user-friendly design, it is convenient to use and easy to install and maintain the charger. Izar also aims to save on energy consumption and costs. It is all about simplicity and convenience to use the Izar AC charger.



en.sinexcel.com



# **Specifications**

Izar CE Home Charger	
Rated Power	7kW
Application Scenarios	Residential
Input/Output Voltage	Single-Phase 230V (±10%)
Input/Output Current	32A
Weight	3.8KG
Protection Rating	IP65/IK10
Dimensions	L336*W299*D120mm
Frequency	50Hz/60Hz
Connector	ІЕС Туре2
Cable Length	5m
Charging Status Information	LED
Charging Mode	Plug and Charge/ RFID / App
Metering	On-board metering (level B, $\pm$ 1%)
Installation	Floor-mounted/ Wall-mounted
Protection Function	Overcurrent protection, overvoltage/undervoltage protection, lightning protection, short circuit protection, ground fault protection (built- in PEN fault device, support UK PEN Fault protection)
Operation Temperature	-30℃-55℃
Operation Altitude	<2000m
Relative Humidity	5%-95%
RCD	DC 6mA
EMC	Class B
Certification	CE/ TUV mark/ RCM/ TR25/ UKCA
Color	White

## en.sinexcel.com



## **Dimensions**



## **Order Now**

Contact us Now! Be among the first to get the latest design

Izar.

#### **Contact Us:**

Shenzhen Sinexcel Electric Co., Ltd Address: Building 6, Zone 2, Baiwangxin Hi tech Industrial Park, No. 1002, Songbai Road, Xili Street, Nanshan District, Shenzhen Company website: https://www.sinexcel.com Tel: 0755-8651-1588/400-0055-776-2



Everything about probability and charging solutions